

929xxx - 2080sc-NTC standard thermistor setup example

Question

How do I set up the 2080sc-NTC from Spectrum Controls for a standard thermistor?

Environment

- 2080SC-NTC

Answer

As an example, a 2080sc-NTC plug-in module is using thermistors with specifications:

- NTC 10k Ω \pm 1% at 25C
- Beta = 3435

An example configuration for channel 0 might look like this:

- S1_CFG_CH_0_Params[0] = 130 decimal (0000 0000 1000 0010b). This equates to a BETA linearization equation, EUX1, 4Hz filter, and channel enabled.
- S1_CFG_CH_0_Params[1] = 20000 (Maximum Range 200.00C)
- S1_CFG_CH_0_Params[2] = 0 (Minimum Range 0.00C)
- S1_CFG_CH_0_string[0] = 3435 (The BETA value)
- S1_CFG_CH_0_string[1] = 10000 (The resistance at 25C)
- S1_CFG_CH_0_string[2] = (Ignored for BETA Equation)

Micro800™ 4 Ch Universal Thermistor Input Module

7

Configuration Tags

This table shows the tags in the sample ladder program for configuration.

Details are described in the sub-sections that follow.

Register	Data Type	Comments
S1_CFG_Trigger	INT	Transition from 0 to non-zero to trigger new config.
S1_CFG_CH_n_Params[0]	INT	Configuration Bits
S1_CFG_CH_n_Params[1]	INT	Maximum Range (default 19016) Degrees C x100 or ohms div 10 Default: 19016
S1_CFG_CH_n_Params[2]	INT	Minimum Range Degrees C x100 or ohms div 10 Default: 0
S1_CFG_CH_n_String[0]	STRING	-COEFF-A for Steinhart-Hart Equation -BETA for BETA Equation
S1_CFG_CH_n_String[1]	STRING	-COEFF-B for Steinhart-Hart Equation -Resistance @25C for BETA Equation
S1_CFG_CH_n_String[2]	STRING	-COEFF-C for Steinhart-Hart Equation Ignored for BETA Equation

For a module in slot 2, set up the Offline Initial Values for channel 0 like this:

Micro850-VAR		NTC_Slot2-POU	
Name	Initial Value	Data Type	Dimension
- S1_CFG_CH_0_Parms	...	INT	[0..2]
S1_CFG_CH_0_Parms[0]	130	INT	
S1_CFG_CH_0_Parms[1]	20000	INT	
S1_CFG_CH_0_Parms[2]	0	INT	
- S1_CFG_CH_0_string	...	STRING	[0..2]
S1_CFG_CH_0_string[0]	'3435'	STRING	
S1_CFG_CH_0_string[1]	'10000'	STRING	
S1_CFG_CH_0_string[2]		STRING	
+ S1_CFG_CH_1_Parms	...	INT	[0..2]
+ S1_CFG_CH_1_string	...	STRING	[0..2]
+ S1_CFG_CH_2_Parms	...	INT	[0..2]
+ S1_CFG_CH_2_string	...	STRING	[0..2]
+ S1_CFG_CH_3_Parms	...	INT	[0..2]
+ S1_CFG_CH_3_string	...	STRING	[0..2]
S1_CFG_Trigger	1	UINT	
S1_Input_CH_0		INT	
S1_Input_CH_1		INT	
S1_Input_CH_2		INT	
S1_Input_CH_3		INT	
S1_STS_CHAN_OC		USINT	
S1_STS_CHAN_OU		USINT	
S1_STS_LED		USINT	
S1_STS_REV_FPGA_0_MAJOR		USINT	
S1_STS_REV_FPGA_1_MINOR		USINT	
S1_STS_REV_MOD_0_MAJOR		USINT	
S1_STS_REV_MOD_1_MINOR		USINT	
S1_STS_REV_MOD_2_BUILD		USINT	
S1_STS_WD_DISABLE		USINT	
Slot_ID	2	UINT	

Your Online Values will look something like this:

Micro850-VAR		NTC_Slot2-POU			
Name	Logical Value	Initial Value	Data Type	Dimension	
- S1_CFG_CH_0_Parms	INT	[0..2]	
S1_CFG_CH_0_Parms[0]	130	130	INT		
S1_CFG_CH_0_Parms[1]	20000	20000	INT		
S1_CFG_CH_0_Parms[2]	0	0	INT		
- S1_CFG_CH_0_string	STRING	[0..2]	
S1_CFG_CH_0_string[0]	3435	'3435'	STRING		
S1_CFG_CH_0_string[1]	10000	'10000'	STRING		
S1_CFG_CH_0_string[2]			STRING		
+ S1_CFG_CH_1_Parms	INT	[0..2]	
+ S1_CFG_CH_1_string	STRING	[0..2]	
+ S1_CFG_CH_2_Parms	INT	[0..2]	
+ S1_CFG_CH_2_string	STRING	[0..2]	
+ S1_CFG_CH_3_Parms	INT	[0..2]	
+ S1_CFG_CH_3_string	STRING	[0..2]	
S1_CFG_Trigger	0	1	UINT		
S1_Input_CH_0	2727		INT		
S1_Input_CH_1	3002		INT		
S1_Input_CH_2	2985		INT		
S1_Input_CH_3	3118		INT		
S1_STS_CHAN_OC	0		USINT		
S1_STS_CHAN_OU	0		USINT		
S1_STS_LED	0		USINT		
S1_STS_REV_FPGA_0_MAJOR	1		USINT		
S1_STS_REV_FPGA_1_MINOR	3		USINT		
S1_STS_REV_MOD_0_MAJOR	1		USINT		
S1_STS_REV_MOD_1_MINOR	1		USINT		
S1_STS_REV_MOD_2_BUILD	7		USINT		
S1_STS_WD_DISABLE	0		USINT		
Slot_ID	2	2	UINT		
Temp_Ambient	29.85		REAL		
Temp_Ambient_Raw	2985		INT		
Temp_Chiller	27.27		REAL		
Temp_Chiller_Raw	2727		INT		
Temp_Floor	31.18		REAL		
Temp_Floor_Raw	3118		INT		
Temp_SP	65.0		REAL		
Temp_Tower	30.02		REAL		
Temp_Tower_Raw	3002		INT		

The 4 temperatures are running in the 27C – 31C range (near ambient).

The last 4 groups of lines in the ST code POU for this example look like this:

```
146
147  (*****)
148  (* Temperature Data *)
149  (*****)
150
151  Temp_Chiller_Raw := (S1_Input_CH_0);
152  Temp_Chiller := ANY_TO_REAL(Temp_Chiller_Raw);
153  Temp_Chiller := (Temp_Chiller/100.0);
154
155  Temp_Tower_Raw := (S1_Input_CH_1);
156  Temp_Tower := ANY_TO_REAL(Temp_Tower_Raw);
157  Temp_Tower := (Temp_Tower/100.0);
158
159  Temp_Ambient_Raw := (S1_Input_CH_2);
160  Temp_Ambient := ANY_TO_REAL(Temp_Ambient_Raw);
161  Temp_Ambient := (Temp_Ambient/100.0);
162
163  Temp_Floor_Raw := (S1_Input_CH_3);
164  Temp_Floor := ANY_TO_REAL(Temp_Floor_Raw);
165  Temp_Floor := (Temp_Floor/100.0);
166
```